

1.4 Product Parameters

There are two versions of scanners of this series, the basic version and document base version. A4 format scanning and A4/A3 format scanning options are available for both versions. The configuration of each model is subject to the actual product.

Basic Parameters

1. Main Camera: 5 to 16 megapixel (Optional), 5 megapixel (2592*2048), 10 megapixel (3264*2448), 10 megapixel (3672*2754), 12 megapixel (4000*3000), 13 megapixel (4160*3120), 14 megapixel (4320*3456), 14 megapixel (4608*3456).
2. A3 version scanning size \leq A3, A4 version scanning size \leq A4; Video format: MJPG (default), YUV (Optional); Picture format: JPG; Image color: color; Output format: JPG, PDF, searchable PDF, Word, Excel.
3. Scanning Light Source: natural light + LED fill light, support auto dimming, 6 levels of brightness.
4. Top LED Fill Light: Color temperature (CCT) 6000-6500 K; color rendering index (CRI Ra) 80-85; illuminance(Lux) \geq 420 Lux.
5. Scanning mode: Supports PC software triggering, and foot pedal.
6. Supports OCR text recognition.
7. Power Adapter (Optional): input 100-240V, 50/60Hz, output 5V/500mA is used for power supply of the document base version; 5V/500mA is used for the power supply of the basic version.

Optional Parameters

1. Second Camera (Optional): single camera 2 megapixels (1920*1080).

2. Third camera (Optional): single camera 2 megapixel (1920*1080).
3. Industry Customized Module (Optional): It can integrate the IC card reader, and signature board according to market demand.
4. Expanded USB ports (Optional): USB Port 2.0 (1 to 4 port options).
5. Face and ID comparison and live detection algorithm (Optional).

1.5 Packaging and Accessories

Basic Version

CZUR Shine \times 1, USB cable \times 1, foot pedal \times 1 (Optional), soft pad \times 1, CD \times 1, User Manual \times 1, Finger cots \times 2.

Document Base Version

Device piece A \times 1, Device piece B, A3 document base(Only A3 model) \times 1, USB cable \times 1, power adapter \times 1, foot pedal \times 1, hexagonal screw and L-shaped screwdriver \times 1, CD \times 1, User Manual \times 1.

Chapter II Operation Guides

2.1 Software Installation

Supports XP/Win7/Win8/Win10, 32-bit/64-bit system, and macOS.

Visit the [Support] section of the official website www.czur.com, select the